




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04B 7/00	A2	(11) International Publication Number: WO 99/09674 (43) International Publication Date: 25 February 1999 (25.02.99)
(21) International Application Number: PCT/US98/16815 (22) International Filing Date: 13 August 1998 (13.08.98) (30) Priority Data: 60/055,549 13 August 1997 (13.08.97) US (71) Applicant (for all designated States except US): QUALCOMM INCORPORATED [US/US]; 6455 Lusk Boulevard, San Diego, CA 92121 (US). (72) Inventor; and (75) Inventor/Applicant (for US only): HERZOG, Rupert [IL/IL]; Qualcomm Israel Ltd., Advance Technology Center, 31905 Haifa (IL). (74) Agents: OGROD, Gregory, D. et al.; Qualcomm Incorporated, 6455 Lusk Boulevard, San Diego, CA 92121 (US).		(81) Designated States: AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GE, GH, GM, HR, HU, ID, IL, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, US, UZ, VN, YU, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG). Published <i>Without international search report and to be republished upon receipt of that report.</i>

(54) Title: METHOD AND APPARATUS FOR INTERFERENCE CANCELLATION FOR A HIGH DATA RATE USER IN A CDMA SYSTEM

(57) Abstract

A method and apparatus for reducing co-channel interference in a CDMA radio telephone system wherein a traffic channel signal is transmitted from a first station (e.g., a base station) (100) in the system to and a second station in the system (e.g., a mobile station) (200). The traffic channel signal contains information representative of a plurality of CDMA data signals each of which is modulated with a different Walsh code prior to transmission of the traffic channel signal from the first station (100) to the second station (200). A reduced interference signal is formed at the second station (200) by subtracting an interference signal from the traffic channel signal. A decoded signal is formed at the second station (200) by decoding information representative of the reduced interference signal using a decoder (260) that outputs a plurality of metric values. The metric values are then used as inputs to a feedback loop (270, 272, 274, 276, 278, 280) that is used to form the interference signal that is subtracted from the traffic channel signal. In this feedback loop (270, 272, 274, 276, 278, 280), an estimated signal is formed in accordance with the plurality of metric values, a plurality of reconstructed CDMA signals are formed from the estimated signal, each of the reconstructed CDMA signals being modulated in accordance with a different one of the Walsh codes, and the reconstructed CDMA signals are then used to form the interference signal.



FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

METHOD AND APPARATUS FOR INTERFERENCE CANCELLATION FOR A HIGH DATA RATE USER IN A CDMA SYSTEM

5

BACKGROUND OF THE INVENTION

I. Field of the Invention

The present invention relates to wireless communications. More specifically, the present invention relates to wireless communication systems that transmit and receive signals between base stations and mobile stations in accordance with code division multiple access (CDMA) modulation. Even more specifically, the present invention relates to a method and apparatus for reducing co-channel interference in a CDMA system in cases where the same user is simultaneously transmitting data on multiple CDMA channels in order to, for example, achieve a high data rate.

II. Description of the Related Art

In multi-code (MC) CDMA radio telephone systems, several CDMA signals associated with a single user may be sent between two stations in order to provide the user with a higher data rate. In such systems, each CDMA signal associated with a single user is spread using direct sequence (DS) spreading and orthogonal Walsh codes, and the spread signals are scrambled using pseudo-noise (PN). However, the transmission quality of the CDMA signals in such systems typically degrades when the signals travel over more than one path between the transmitter and the receiver. This is because such "multi-path propagation" causes co-channel interference between the transmitted CDMA signals. The present invention is directed to a method and apparatus for reducing (or canceling) such co-channel interference.

SUMMARY OF THE INVENTION

Disclosed herein is a method and apparatus for reducing co-channel interference in a CDMA radio telephone system. The disclosed system transmits a traffic channel signal from a first station (e.g., a base station) to and a second station (e.g., a mobile station). The traffic channel signal contains a plurality of CDMA data signals, each data signal modulated with a different Walsh code prior to transmission of the traffic channel signal from a first station to a second station. In one embodiment of the

disclosed system, the traffic channel signal contains a plurality of CDMA data signals associated with a single user. Each of the CDMA data signals associated with the single user is modulated with a different Walsh code prior to transmission of the traffic channel signal from the first station to the second station. Use of the plurality of CDMA data signals for the single user facilitates transmission of data at a relatively high data rate for the single user, because such signals permit the simultaneous transmission of data associated with the single user on multiple CDMA channels.

In accordance with the preferred embodiment of the disclosed method and apparatus, a "reduced interference signal" is formed at the second station in an iterative fashion by subtracting an interference signal from the traffic channel signal. A "decoded signal" is formed at the second station by decoding information represented by the reduced interference signal using a decoder (e.g., a convolutional or turbo decoder) that outputs a plurality of metric values. It should be noted that the first iteration has no correction. The metric values are then used as inputs to a feedback loop that is used to form the interference signal that is subtracted from the traffic channel signal. In this feedback loop: (1) an estimated signal is formed in accordance with the plurality of metric values; (2) plurality of reconstructed CDMA signals are formed from the estimated signal; (3) each of the reconstructed CDMA signals being modulated in accordance with a different one of the Walsh codes; and (4) the reconstructed CDMA signals are combined, scrambled and filtered to form the interference signal.

BRIEF DESCRIPTION OF THE DRAWINGS

The features, objects and advantages of the present invention will become more apparent from the detailed description set forth below when taken in conjunction with the drawings in which like reference characters identify correspondingly throughout and wherein:

Figure 1 is a block diagram of a remote station (e.g., a base station) that encodes, processes and transmits CDMA signals in accordance with the present invention.

Figure 2 is a block diagram of a remote station (e.g., a mobile station) that receives, demodulates and decodes CDMA signals in a manner that reduces co-channel interference, in accordance with the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Disclosed herein is a method and apparatus for reducing co-channel interference in a CDMA radio telephone system. The present invention is included within the disclosed method and apparatus. However, the scope of the invention is to be determined solely by the limitations of the claims appended hereto, and not by the limitations of the disclosed method and apparatus.

Figure 1 is a block diagram of a remote station 100 (e.g., a base station) that encodes, processes and transmits CDMA signals in accordance with the disclosed method and apparatus. A "data information signal" (b) from a single user operating at an increased data rate is provided to a convolutional encoder 110 in order to form an "encoded data signal" (c). Encoder 110 encodes the data information signal in accordance with a convolutional coding algorithm or a parallel concatenated convolutional coding algorithm (i.e., a "turbo" code) with code rate R_c . One example of a code that may be used for encoding by encoder 110 is a terminated non-systematic convolutional code (CC) with a code rate $R_c = 1/2$ and memory $m = 4$, defined by the generator matrix set forth in equation (1) below:

$$G_{cc4}(D) = (1 + D^3 + D^4 \quad 1 + D + D^2 + D^4) \quad (1)$$

A second exemplary code that may be used for encoding by encoder 110 is a terminated CC having memory $m = 8$, defined by the generator matrix set forth in equation (2) below:

$$G_{cc8}(D) = (1 + D + D^2 + D^3 + D^5 + D^7 + D^8 \quad 1 + D^2 + D^3 + D^4 + D^8) \quad (2)$$

A third exemplary code that may be used for encoding by encoder 110 is a parallel concatenated convolutional code (PCC) (also known as a turbo code) which consists of two equal systematic component codes, defined by the generator matrix set forth in equation (3) below:

$$G_{PCC}(D) = (1 \quad (1 + D^4)/(1 + D + D^2 + D^3 + D^4)) \quad (3)$$

The resulting code rate of this third exemplary code is $R_c = 1/3$. Thus, the code rate of the exemplary PCC is 1.5 times slower than that of the exemplary CC's set forth above. Given a constant user data rate, the lower code rate requires a 1.5 times greater number of assigned traffic channels (N_T) than that required when the exemplary CC's are used.

It will be understood by those skilled in the art that additional coding algorithms other than the three examples set forth above may alternatively be used.

The encoded data signal (c) from encoder 110 is provided to a channel interleaver (il) 120. Interleaver 120 consists of N_T block

interleavers (not shown) each of which corresponds to one of the N_T traffic channels. In a preferred embodiment, each of the N_T block interleavers has a block size of 384 codebits (i.e., 20 ms at 19.2 kbps). Prior to the interleaving, the code bits from the encoded data signal (c) are demultiplexed to the N_T traffic channels in the following way: The first contiguous block of 384 code bits from the encoded data signal (c) are provided to the block interleaver corresponding to a first traffic channel c_1 , the next contiguous block of 384 code bits from the encoded data signal (c) are provided to the block interleaver corresponding to a second traffic channel c_2 , and so on such that the N_T th contiguous block of 384 code bits from the encoded data signal (c) are provided to the block interleaver corresponding to a N_T th traffic channel c_{N_T} . This demultiplexing method ensures that subsequent code bits are not transmitted at the same time.

The N_T interleaved signals output by the block interleaver 120 are provided to modulation units 130, where each of the interleaved signals is multiplied with a Walsh sequence (w_i). In a preferred embodiment, the outputs of the modulation units are fixed rate signals having a chip rate of 1.2288 Mcps. The set of Walsh codes preferably consists of 64 binary sequences (each with a length of $W=64$) which are orthogonal to each other and provide ideal channel separation at the receiver in the absence of multipath propagation. The modulation units 130 output a plurality of spread signals that are combined using summer 140 to form a composite signal that is output from summer 140. As shown in Figure 1, the signals input to summer 140 may optionally include spread signals associated with users other than the signal user associated with data information signal (b). The composite signal output from summer 140 is applied to a scrambler 150 which scrambles the inphase and quadrature components of the composite signal using pseudo-noise (PN) to form a scrambled signal. The scrambled signal is then normalized to form a traffic channel signal (x) by multiplying the scrambled signal with an amplitude factor $(E_c)^{1/2}$, where E_c is the transmitted energy per chip of the traffic channel signal.

Figure 2 is a block diagram of a remote station 200 (e.g., a mobile station) that receives, demodulates and decodes CDMA signals in a manner that reduces co-channel interference, in accordance with the disclosed method and apparatus. The traffic channel signal (x) is transmitted from remote station 100 to remote station 200 over a traffic channel having an impulse response characteristic ($h(k)$). Upon reception at remote station 200, noise is added to the signal due to the physics of, and imperfections in, the receiver. The resulting signal (y) is applied to a filter 210 which has an impulse response characteristic ($f(k)$) that is matched to

the impulse response of the traffic channel, i.e., $f(k) = h^*(-k)$. The output traffic channel signal from filter 210 is denoted in Figure 2 as signal (z).

The traffic channel signal (z) and an interference signal (z_i) are applied to a signal subtracting unit 220 which subtracts the interference signal (z_i) from the traffic channel signal (z). The output of the subtracting unit 220 is applied to descrambling units 230, 232. Descrambling unit 230 multiplies the output of the subtracting unit 220 by the complex conjugate of the scrambling sequence used by scrambler 150. Unit 232 then takes the real part of the signal output from unit 230 to form a descrambled signal (q). The descrambled signal (q) is applied to a signal processor 240 that applies a Fast-Hadamard Transform (FHT) to the descrambled signal (q) so as to correlate the descrambled signal (q) with each of the Walsh functions used by modulators 130. The output of signal processor 240 is a plurality of de-spread signals (r_1, r_2, \dots, r_{NT}), each of which corresponds to one of the Walsh functions used by modulators 130. Next, the de-spread signals (r_1, r_2, \dots, r_{NT}) are applied to a de-interleaver (de-il) 250, which performs the inverse of the operation performed by interleaver 120 in order to form a de-interleaved signal (r).

The de-interleaved signal is applied to decoder 260 in order to form a decoded output signal. In accordance with one embodiment of the disclosed invention, the decoder 260 is a log-MAP decoder that uses a convolutional or turbo decoding algorithm which is the inverse of the encoding algorithm used by encoder 110. However, it will be understood by those skilled in the art that the decoder 260 may be any decoder that is capable of outputting metrics that indicate the quality of the decoded signal. The decoder 260 outputs soft decision log-likelihood metrics ($L(c)$) for the coded bits. If that encoder 110 used a CC for encoding the bits, decoding is performed at decoder 260 using a symbol-by-symbol log-MAP decoder. If encoder 110 used a turbo code for encoding the bits, decoder 260 preferably performs iterative decoding (for example 6 iterations) using a symbol-by-symbol log-MAP decoder.

The metrics ($L(c)$) from decoder 260 are applied to a further signal processor 270 which applies a non-linear saturation function (e.g., $\tanh((L(c))/2)$) to the metrics in order to form an estimated signal (c). The estimated signal (c) from signal processor 270 is provided to a channel interleaver (il) 272 which outputs a plurality of interleaved estimated signals. Interleaver 272 corresponds substantially to interleaver 120, and consists of N_T block interleavers (not shown), each of which corresponds to one of the N_T traffic channels.

The N_T interleaved estimated signals output by the block interleaver 272 are provided to modulation units 274, where each of the interleaved estimated signals is multiplied with a different one of the Walsh sequences (w_i) used by modulation units 130. The modulation units 274 output a plurality of estimated CDMA spread signals that are combined using summer 276 to form a composite estimated signal that is output from summer 276. The composite estimated signal output from summer 276 is applied to a scrambler 278 which scrambles the inphase and quadrature components of the composite signal using pseudo-noise (PN) to form an estimated scrambled signal. Scrambler 278 functions substantially in accordance with scrambler 150. The estimated scrambled signal is then normalized to form a reconstructed signal (x_1) by multiplying the estimated scrambled signal with the amplitude factor $(E_c)^{1/2}$ discussed above.

Finally, the interference signal (z_1) is formed by applying filter 280 to the reconstructed signal (x_1). Filter 280 preferably has an impulse response characteristic ($g(k)$) that is equal to $(h(k)*f(k))$ for all non-zero values of k , and the impulse response characteristic ($g(k)$) of filter 280 is equal to zero when k is zero.

The previous description of the preferred embodiments of the disclosed method and apparatus is provided to enable any person skilled in the art to make or use the claimed invention, which is included within the disclosed method and apparatus. The various modifications to these embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without the use of inventive faculty. Thus, the present invention is not intended to be limited to the disclosed method and apparatus shown herein, but is to be determined solely by the claims set forth below.

I CLAIM:

CLAIMS

1. A method for reducing co-channel interference in a code
2 division multiple access (CDMA) radio telephone system wherein a traffic
channel signal is transmitted from a first station in the system to and a
4 second station in the system, comprising the steps of:

(a) forming a reduced interference signal at the second
6 station by subtracting an interference signal from the traffic channel signal,
wherein the traffic channel signal contains information representative of a
8 plurality of CDMA data signals each of which is modulated with a
different Walsh code prior to transmission of the traffic channel signal
10 from the first station to the second station;

(b) forming a decoded signal at the second station by
12 decoding information representative of the reduced interference signal
using a decoder that outputs a plurality of metric values;

(c) forming an estimated signal in accordance with the
14 plurality of metric values, and then forming the interference signal from
the estimated signal, wherein the step of forming the interference signal
16 includes the step of forming a plurality of reconstructed CDMA signals
from the estimated signal, each of the reconstructed CDMA signals being
18 modulated in accordance with a different one of the Walsh codes.

2. The method of claim 1, wherein the traffic channel signal
2 contains information representative of a plurality of CDMA data signals
associated with a single user transmitted from the first station to the
4 second station, and each of the CDMA data signals associated with the
single user is modulated with one of the different Walsh codes prior to
6 transmission of the traffic channel signal from the first station to the
second station.

3. The method of claim 2, wherein the decoder used in step (b)
2 is a convolutional decoder or a turbo decoder.

4. The method of claim 3, wherein the step of forming the
2 interference signal further includes the step of combining the
reconstructed CDMA signals.

5. The method of claim 4, wherein the traffic channel signal is
2 formed at the first station prior to transmission of the traffic channel
signal from the first station to the second station, and the step of forming
4 the traffic channel signal at the first station comprises the steps of:

(i) applying a data signal associated with the
6 single user to a convolutional encoder to form an encoded data signal, and
then applying the encoded data signal to an interleaver to form a plurality
8 of interleaved signals associated with the single user;

(ii) multiplying each of the interleaved signals
10 with a different one of the Walsh codes to form a plurality of spread
signals associated with the single user;

(iii) forming a composite signal by combining
12 the plurality of spread signals associated with the single user; and

(iv) scrambling the composite signal with
14 pseudo-noise (PN) sequences.

6. The method of claim 5, wherein the interleaver is formed of
2 a plurality of block interleavers, and each of the block interleavers outputs
one of the plurality of interleaved signals associated with the single user.

7. The method of claim 6, wherein the step of applying the
2 encoded data signal to the block interleavers comprises demultiplexing the
encoded data signal such that a first contiguous block of code bits from the
4 encoded data signal are input to a first of the block interleavers, a second
contiguous block of code bits from the encoded data signal are input to a
6 second of the block interleavers, and a third contiguous block of code bits
from the encoded data signal are input to a third of the block interleavers,
8 wherein the first contiguous block of code bits immediately precedes the
second contiguous block of code bits in the encoded data signal, and the
10 third contiguous block of code bits comes after the first and second
contiguous blocks of code bits in the encoded data signal.

8. The method of claim 5, wherein step (iii) comprises forming
2 the composite signal by combining the plurality of spread signals
associated with the single user and at least one signal associated with a
4 second user.

9. The method of claim 5, wherein step (iv) comprises
2 scrambling in-phase and quadrature components of the composite signal
with PN sequences.

10. The method of claim 5, wherein the different Walsh codes
2 represent a set of Walsh codes, and each Walsh code in the set is
orthogonal to all other Walsh codes in the set.

11. The method of claim 5, wherein the convolutional encoder
2 encodes the data signal in accordance with a convolutional code selected
from the group consisting of convolutional codes, concatenated codes, and
4 turbo codes.

12. The method of claim 4, further comprising the step of
2 filtering the traffic channel signal prior to subtracting the interference
signal from the traffic channel signal.

13. The method of claim 12, wherein the traffic channel signal is
2 transmitted from the first station to the second station along a traffic
channel having a first impulse response characteristic, and the filtering
4 step comprises applying a filter having a second impulse response
characteristic to the traffic channel signal, wherein the second impulse
6 response characteristic is matched to the first impulse response
characteristic.

14. The method of claim 4, wherein step (b) comprises the steps
2 of:

(i) descrambling the reduced interference signal
4 to form a descrambled signal;

(ii) forming a plurality of de-spread signals from
6 the descrambled signal by correlating the descrambled signal with each of
the different Walsh codes;

(iii) forming a decoder input signal by de-
8 interleaving the de-spread signals; and

(iv) forming the decoded signal at the second
10 station by decoding the decoder input signal using the convolutional
decoder that outputs the plurality of metric values.
12

15. The method of claim 14, wherein the convolutional decoder
2 decodes the decoder input signal in accordance with a convolution code
selected from the group consisting of convolutional codes, concatenated
4 codes, and turbo codes.

16. The method of claim 4, wherein the step of forming an
2 estimated signal in accordance with the plurality of metric values
comprises the step of applying the metric values to a saturation function.

17. The method of claim 16, wherein the saturation function is a
2 non-linear saturation function.

18. The method of claim 17, wherein the saturation
2 function provides soft values for the cancellation.

19. The method of claim 4, wherein the step of forming the
2 plurality of reconstructed CDMA signals from the estimated signal
comprises the steps of applying the estimated signal to an interleaver to
4 form a plurality of interleaved estimated signals, and multiplying each of
the interleaved estimated signals with a different one of the Walsh codes
6 to form a plurality of estimated spread signals.

20. The method of claim 19, wherein the step of combining the
2 reconstructed CDMA signals comprises the steps of forming a composite
estimated signal by combining the plurality of estimated spread signals,
4 and scrambling the composite estimated signal with pseudo-noise (PN)
sequences to form an estimated scrambled signal.

21. The method of claim 20, wherein the step of scrambling the
2 composite estimated signal with PN sequences comprises scrambling in-
phase and quadrature components of the composite estimated signal with
4 PN sequences.

22. The method of claim 20, further comprising the step of
2 forming the interference signal by filtering the estimated scrambled signal.

23. The method of claim 22, further comprising the step of
2 filtering the traffic channel signal prior to subtracting the interference
signal from the traffic channel signal, wherein the traffic channel signal is
4 transmitted from the first station to the second station along a traffic
channel having a first impulse response characteristic ($h(k)$), and the
6 filtering step comprises applying a filter having a second impulse response
characteristic ($f(k)$) to the traffic channel signal, wherein the second
8 impulse response characteristic ($f(k)$) is matched to the first impulse
response characteristic ($h(k)$).

24. The method of claim 23, wherein the step of filtering the
2 estimated scrambled signal comprises filtering the estimated scrambled
signal with an interference cancellation filter having a third impulse
4 response characteristic ($g(k)$).

25. The method of claim 24, wherein the third impulse response
2 characteristic ($g(k)$) is equal to $(h(k)*f(k))$ for all non-zero values of k , and
the third impulse response characteristic ($g(k)$) is equal to zero when k is
4 zero.

26. An apparatus for reducing co-channel interference in a code
2 division multiple access (CDMA) radio telephone system wherein a traffic
channel signal is transmitted from a first station in the system to and a
4 second station in the system, comprising:

(a) means for forming a reduced interference signal at the
6 second station by subtracting an interference signal from the traffic
channel signal, wherein the traffic channel signal contains information
8 representative of a plurality of CDMA data signals each of which is
modulated with a different Walsh code prior to transmission of the traffic
10 channel signal from the first station to the second station;

(b) means for forming a decoded signal at the second
12 station by decoding information representative of the reduced interference
signal using a decoder that outputs a plurality of metric values;

(c) means for forming an estimated signal in accordance
14 with the plurality of metric values;

(d) means for forming the interference signal from the
16 estimated signal, wherein the means for forming the interference signal
includes means for forming a plurality of reconstructed CDMA signals
18 from the estimated signal, each of the reconstructed CDMA signals being
20 modulated in accordance with a different one of the Walsh codes.

27. An apparatus for reducing co-channel interference in a code
2 division multiple access (CDMA) radio telephone system wherein a traffic
channel signal is transmitted from a first station in the system to and a
4 second station in the system, comprising:

(a) a signal subtractor that forms a reduced interference
6 signal at the second station by subtracting an interference signal from the
traffic channel signal, wherein the traffic channel signal contains
8 information representative of a plurality of CDMA data signals each of

which is modulated with a different Walsh code prior to transmission of
10 the traffic channel signal from the first station to the second station;

(b) a decoder that forms a decoded signal at the second
12 station by decoding information representative of the reduced interference
signal using a decoding algorithm that outputs a plurality of metric values;

(c) a signal estimator that forms an estimated signal in
14 accordance with the plurality of metric values;

(d) a signal reconstructor that forms the interference signal
16 from the estimated signal, wherein the signal reconstructor includes at
least one modulator for forming a plurality of reconstructed CDMA signals
18 from the estimated signal, each of the reconstructed CDMA signals being
20 modulated in accordance with a different one of the Walsh codes.

1/2




FIG. 1

2/2




FIG. 2